


STORM

LONDON

PHERIC




A: Light B: Mode C: Reset D: Date/Start/Stop

FEATURES

- 4 digit LCD display
- Display functions:

Time	Hours, minutes, seconds, 12Hr/24Hr.
Calendar	Day, date, month, year, perpetual calendar.
Alarm	Daily alarm and hourly chime.
Stop watch	1/100 second chronograph with double split function.
Light	Light up screen while in any mode.
Button tone	Tone sounds when button pressed.

SETTING SEQUENCE



VIEWING THE DAY/DATE

Press 'B' until in Time mode.
Press and hold 'D' to view Day, Month and Date.

SETTING THE TIME AND DATE

Press 'B' until in Time mode.
Press and hold 'C' until 2nd beep sounds and digits flash.
Press 'D' to change minute.
Press 'B' to advance to hour digits.
Press 'D' to change hour.
Repeat until entire sequence is correct. See below.
Press 'C' to exit back to Time mode.



SETTING THE ALARM

Press 'B' until in Alarm mode. (ALM)
Press and hold 'C' until 2nd beep sounds and digits flash.
Press 'D' to change minute.
Press 'B' to advance to hour digits.
Press 'D' to change hour.
Press 'C' to confirm.

Press 'D' to turn alarm and daily chime On/Off.
If a 'BELL' symbol is visible, the Alarm is On.
If all the days of the week are visible, the Hourly Chime is On.

USING THE LIGHT

Press 'A' once in any mode to light up the screen.
Press and hold 'A' to extend the time that the light is on.
NB. Using the light will use up more battery power.

USING THE CHRONOGRAPH

Press 'B' until in Chronograph mode. (SPL)
Press 'D' to Start and Stop timer.
Press 'C' to reset back to zero.

SPLIT TIME

Press 'D' to Start timer.
Press 'C' to freeze screen. Timer continues to run.
Press 'C' to unfreeze the screen. Timer shows time from start.
Freeze and unfreeze screen as required.
Press 'D' to stop timer completely.
Press 'C' to reset.

WHEN RECORDING TWO DIFFERENT FINISH TIMES

Press 'D' to Start timer.
Press 'C' to freeze screen (1st finish). Timer continues to run.
Press 'D' to stop timer (2nd finish).
Screen still shows frozen time (1st finish).
Press 'C' to view final recorded time (2nd finish).
Press 'C' to reset.

